

-EXPERIENCE electronics- power transformer data sheet NTR-12 C

Special power transformer for high end hifi power amps and preamps. On secondary three taps enable the use of diifferent tube types. Heating is possible in AC or DC mode. Two taps enable higher or lower negative grid 1 voltages for different tube types.

Power handling	320 VA	pinning
Primary	115 V 115 V	(1-2) (3-4)
Protection	static shield between primary and secondary connected to core	
Secondary 1	340 V/0.6 A	(6-7)
Secondary 2	390 V/0.6 A	(6-8)
Secondary 3	410 V/0.6 A	(6-9)
Secondary 4	40 V/0.05 A	(10-11)
Secondary 5	60 V/0.05 A	(10-12)
Secondary 6	22 V/0.05 A	(13-14)
Secondary 7	6.3V /6 A	(15-16)
Secondary 8	6.3 V/6 A	(17-18)
Secondary 9	18 V/0.2 A	(19-20)
Secondary 10	18 V/0.2 A	(22-23)
Core type	MD 102 B	
Dimensions	length	120 mm
	width	102 mm
	height	89 mm
Mounting	bolts M 5	
Weight	ca. 5.1 kg	
Connectors	solder lugs	

